



Call2Prayer 2.0

Customer Instructions

Getting Started

Thank you for purchasing Call2Prayer 2.0, the small but mighty Islamic companion designed to enrich your daily spiritual routine. To get started, connect it to power, switch it on and scan the QR code displayed on the device. Follow the on-screen instructions to connect Call2Prayer 2.0 to your home WiFi network. **Please note: Call2Prayer 2.0 supports 2.4 GHz WiFi networks only.**

Warranty

Call2Prayer 2.0 includes a **3-month warranty** from the date of purchase.

SD Card Warranty

The included SD card has a **1-month warranty** from the date of purchase.

Important Reset Instructions

Forgotten Portal Password

Power on Call2Prayer. When the Call2Prayer logo appears, hold the physical volume button for at least **15 seconds**, then release it before 30 seconds. This clears only the Portal username and password. WiFi, prayer times, alarms and all other settings remain unchanged.

Factory Reset

Power on Call2Prayer. When the Call2Prayer logo appears, hold the physical volume button continuously for **30 seconds**. The screen shows the reset stages.

Using Call2Prayer 2.0

- 1. Home:** Shows the date, time, Islamic date, next prayer and the audio bar when an Azan is playing. A red Islamic date indicates a Shahadat, while a green Islamic date indicates a Wiladat. On a Shahadat or Wiladat, press the Islamic date to open that event in the Islamic Calendar. Press the next prayer name to view the selected Azan reciter and reminder details.
- 2. Quick Settings:** Swipe down from the top of the screen to access Quick Settings, which shows the device's current timezone and controls for WiFi, brightness, restart, torch, always on display and Night Mode.
- 3. Page Navigation:** Swipe left or right to move between pages. Tap three times near the top on any device page to return Home.
- 4. Azan & Reminders:** Select the Azan and reminder for Fajr, Zohr and Maghrib each day.
- 5. Quran:** Select the Qari and Surah, then use play, pause and stop.
- 6. Duas:** Select the reciter and Dua, then use play, pause and stop.
- 7. Tasbih:** Tap the counter to count tasbih. Reset clears the current count.

Settings & Connection

- 8. Short Duas:** Read short duas with Arabic, transliteration and meaning.
- 9. Settings:** The device Settings page has volume, brightness and the QR code for the Parent Portal.
- 10. Auto WiFi Connect:** When Call2Prayer starts, it tries to connect to its saved WiFi network for up to 30 seconds. If the connection fails, it automatically enters WiFi Setup mode while continuing to retry the saved network. Connect your phone to the C2P-Setup network, open 192.168.4.1 and select your WiFi network if needed.
- 11. Portal Address:** Use the address shown on the device to access the Parent Portal from phones and computers connected to the same WiFi. If it does not open on a particular phone or router, scan the QR code on the device and use the IP address shown as the backup. If it still does not open, restart Call2Prayer.
- 12. Physical Buttons:** The physical button closest to the charging port is the power button. The button next to it controls the volume.
- 13. Volume Controls:** Press the volume button once to increase the volume. Rapidly double press it to decrease the volume.
- 14. Night Mode:** Under Night Mode in Device Settings on the Parent Portal, choose a text colour using the colour wheel, adjust its intensity and press Save Night Mode. The saved appearance is used whenever Night Mode is turned on from Quick Settings.

Calendar, Reminders & SD Card

15. Calendar: The Calendar page shows both the English (Gregorian) and Islamic calendars. The Islamic calendar is derived from date calculations, and its date can be increased or decreased from the Calendar settings in the Parent Portal.

16. Reminders: For each prayer, a selected Surah from a Quran Qari, a Dua from an available reciter, or the Standard Original Reminder can be played before the Azan.

17. Scheduled Recitations: Choose a Quran Surah or Dua, its Qari or reciter, the time and repeat days.

18. Battery Estimate: The battery percentage shown in the Parent Portal and on Call2Prayer is an estimate based on battery voltage. It may not always match the exact real charge level, and while charging it can stay around 98% or 99% for some time before reaching full.

19. Unauthorised Files on the SD Card: Do not add, remove or rename files directly on the SD Card. If Call2Prayer detects unauthorised content, normal operation pauses and the SD Card Recovery screen appears. Keep Call2Prayer powered on, scan the QR code or open the displayed Portal address, review the detected entries and press Remove Unauthorised Files. Call2Prayer removes those entries, verifies the SD Card and restarts automatically.

Keep this guide available for setup, everyday use and troubleshooting.